

SL-5500 v3 Upgrade Guide

Introduction

The SL-5500 v3 Upgrade provides current SL-5500 users with the ability to experience the software provided on the recently released SL-5600 Zaurus. Key features of the SL-5500 v3 Upgrade include:

- Faster and improved synchronization
- Synchronization of eMail attachments
- Updated Email client with separate folders for each account
- Opera 6.0 browser
- Updated Address Book with user configurable column headings
- Updated Calendar with additional new views and improved support for all-day and multi-day events
- New Zaurus File Transfer with simple drag-and-drop file movement
- Integrated File manager (replaces Documents Tab)
- Extended MP3 playback with display off feature
- Backup/Restore the Zaurus with your PC

Comparison of Zaurus SL-5500 and v3 Upgrade Software

Application	SL-5500	SL-5500 v3 Upgrade	Comments
Applications Tab			
Address Book			Updated to SL-5600 version
Calculator			Updated to SL-5600 version
Calendar			Updated to SL-5600 version
City Time			Updated to SL-5600 version
Clock			Updated to SL-5600 version
EEmail			Updated to SL-5600 version

Application	SL-5500	SL-5500 v3 Upgrade	Comments
HancomPresenter	I	E	Updated to SL-5600 version
HancomSheet	I	E	Updated to SL-5600 version
HancomWord	I	E	Updated to SL-5600 version
Help Browser	I	I	Updated to SL-5600 version
Image Viewer	I	Image Pad	Updated to SL-5600 version
Media Player	I	I	Updated to SL-5600 version
Opera Browser	I	I	Updated to SL-5600 version
System Info	I	I	Updated to SL-5600 version, moved to Settings tab
Text Editor	I	I	Updated to SL-5600 version
Todo List	I	I	Updated to SL-5600 version
Voice Recorder	I	I	Updated to SL-5600 version
Games Tab			
Asteroids	I	E	Updated to SL-5600 version
Go	I	E	Updated to SL-5600 version
Mindbreaker	I	E	Updated to SL-5600 version
Mine Hunt	I	E	Updated to SL-5600 version
Patience	I	I	Updated to SL-5600 version
Snake	I	E	Updated to SL-5600 version
Word Game	I	E	Updated to SL-5600 version
Jeode Tab			
Jeode JVM	I	E	Updated to SL-5600 version
PrimTest	I	E	Updated to SL-5600 version
Quasar	I	E	Updated to SL-5600 version
Settings Tab			
Add/Remove Software	I	I	Updated to SL-5600 version
Appearance	I	I	Updated to SL-5600 version
Application Key	I	I	Updated to SL-5600 version
Backup Restore	I	I	Updated to SL-5600 version
Beam Receive	I	I	Updated to SL-5600 version
Date/Time	I	I	Updated to SL-5600 version

Application	SL-5500	SL-5500 v3 Upgrade	Comments
Internet Wizard	I	I	Updated to SL-5600 version, Integrated into Network
Light & Power	I	I	Updated to SL-5600 version
Network & Sync	I	I	Updated to SL-5600 version, Now called Network
PC Link	N/A	I	Not in original SL-5500 software
Proxim Configuration	I	X	Updated to SL-5600 version, Not supported in upgrade
Recalibrate	I	I	Updated to SL-5600 version
Security	I	I	Updated to SL-5600 version
Shutdown	I	I	Updated to SL-5600 version
Tab Setting	N/A	I	Not in original SL-5500 software
Update ROM	N/A	I	Not in original SL-5500 software *1
Wireless LAN	I	I	Updated to SL-5600 version, Integrated into Network
Documents Tab	I	I	Renamed to Files Tab
Additional Zaurus Software			
Camera	E	E	Updated to SL-5600 version
File Manager	E	E	Updated to SL-5600 version
Terminal	E	E	Updated to SL-5600 version

I = Internal, built-in the System ROM upgrade

E = External, provide with the System ROM but must be installed separately

X = not provided in the System ROM upgrade

*1 This application is included in the SL-5500 v3 Upgrade and may be used to update the internal Flash ROM.

Description/Function Comparison List

The online manual stored in PDF format on the accompanying CD-ROM gives the information about the SL-5600. Please read the following explanation to understand the differences between the SL-5600 and SL-5500 v3 Upgrade.

All Manuals

SL-5600	SL-5500 v3 Upgrade
SL-5600	Read as SL-5500 v3 Upgrade version.
Internal Flash memory	Changed to Internal Storage.
Functions and descriptions (icons, tabs, etc.) about Jeode	Jeode must be installed from the CD-ROM separately. Ignore all relative description about Jeode for default settings.
Design of the front keys	The design of the front keys are different from the SL-5600.
HancomMobileWord, HancomMobileSheet, Games (Asteroids/Go/Mindbreaker/Mine Hunt/Snake/Word Game) and Java applications (Jeode/PrimTest/Quaser)	Install separately from the CD-ROM. See "How to Install Applications on Your SL-5500" on page 8.
Functions and descriptions about built-in speaker and microphone	The built-in speaker and microphone are not supported in the SL-5500. Ignore all relative functions and descriptions. If you want to record voice, attach a commercially available microphone (diameter of the plug: 3.5 mm) to the stereo headphone jack.
Launching the Voice Recording by pressing the Calendar key	It is impossible to launch the Voice Recorder by pressing the Calendar key. Ignore all relative descriptions.
Format function in the Maintenance menu	No Format function. See "Performing a FULL RESET" in Start-up Guide instead of Format.

Operation Manual

SL-5600			SL-5500 v3 Upgrade
Page	Line	Contents	
Cover Page		Name and picture of the unit	The name and picture is different.
2	8	Design of the HOME key	The design of the HOME key is different.
57	4	Description about built-in speaker	You cannot hear the media sound from the built-in speaker.
57	11	Description about sound heard from headphone	No built-in speaker. Ignore this sentence.
66	14	Opera Browser screen	The picture of the Opera Browser screen is different.
115	3	Recording audio files by built-in microphone and playing the recorded data from built-in speaker	No built-in microphone and speaker. Ignore this sentence. If you want to record voice, attach a commercially available microphone (diameter of the plug: 3.5 mm) to the stereo headphone jack.
118	8	Launching the Recorder with the Calendar key	It is impossible to launch the Voice Recorder by pressing the Calendar key. Ignore all relative descriptions.
119	2	Description about built-in speaker	You cannot hear recorded data from the built-in speaker.
120	14	Turn on by Calendar key checkbox (also checkbox on screen)	It is impossible to launch the Voice Recorder by pressing the Calendar key. Ignore this checkbox.
129	1	Games of Asteroids, Go, Mindbreaker, Mine Hunt, Snake and Word Game	Install separately from the CD-ROM. See "How to Install Applications on Your SL-5500" on page 8.
142	4	Illustrations on Set Application Key screen	Illustrations on Set Application Key screen is different.
143	17	Description about storage area	Internal Storage is used instead of Internal Flash. Ignore this sentence.
145	4	The SL-5600 can transfer data with SL-5500.	Data can be transferred from both the SL-5500 and SL-5600.

SL-5600			SL-5500 v3 Upgrade
Page	Line	Contents	
154	6	Description about Format function	No Format function. Ignore this sentence. See “Performing a FULL RESET” in Start-up Guide instead of Format.
158		Description about Sound Settings	No Sound Settings. Ignore all relative descriptions.
160	21	Description about Internal Flash memory	Internal Storage is used instead of Internal Flash. Ignore this sentence.
161	8	Description about information on memory fragmentation	Ignore all relative descriptions.

HancomMobileOffice Operation Manual

SL-5600			SL-5500 v3 Upgrade
Page	Line	Contents	
8	1	HancomMobileWord	Install separately from the CD-ROM. See “How to Install Applications on Your SL-5500” on page 8.
8	9	Screen about Applications tab	No Jeode tab.
26	1	HancomMobileSheet	Install separately from the CD-ROM. See “How to Install Applications on Your SL-5500” on page 8.
68	1	HancomMobilePresenter	Install separately from the CD-ROM. See “How to Install Applications on Your SL-5500” on page 8.
68	15	Screen about Application tab	No Jeode tab.
71	1	Illustration about Menu key	The design of the Menu key is different.

Backup/Restore application

SL-5600			SL-5500 v3 Upgrade
Page	Line	Contents	
6	20	Description about backup	Internal Storage is used instead of Internal Flash. Ignore this sentence.

Camera/File Manager/Terminal

SL-5600			SL-5500 v3 Upgrade
Page	Line	Contents	
1		Installation of each application	Install separately from the CD-ROM. See "How to Install Applications on Your SL-5500" on page 8.
1		Description about Format function	No Format function. See "Performing a FULL RESET" in Start-up Guide instead of Format.

How to Install Applications on Your SL-5500

1. Check that the Zaurus File Transfer application installed correctly.
2. If the SL-5500 and PC are not already connected, connect them using the Docking Station (see the section on “Connecting the SL-5500 to your PC” in the Start-up Guide).

Note:

- *When communicating with the PC, do not perform any operations on the device, turn off the power, remove it from the Docking Station, or disconnect the cable from the PC.*
 - *While communicating with the PC, the AC adapter must be connected.*
3. Double-click on the CD-ROM drive name (example: D) in the My Computer application on your PC.
The menu screen will be displayed automatically. You can also display the menu by ejecting the CD-ROM, then reinserting it.
 4. Click “Additional Software for the Zaurus”.
A window will open, displaying the Applications folder on the CD-ROM.
 5. Next, display the SL-5500 memory window.
Click the Start menu, then (All) Programs → Sharp Zaurus 2 → Zaurus File Transfer → Zaurus File Transfer.
The Zaurus File Transfer application window will appear on the desktop.
The SL-5500 memory will be displayed on the PC using the Zaurus File Transfer application.
The “Internal Flash” folder displays the internal memory of the SL-5500. When a memory card is installed, a “SD Card” or “CF Card” folder will appear.
 6. Double-click the “Internal Flash” folder, then double-click “Install_Files”.
 7. Drag the file of the Applications folder from the CD-ROM and drop it into the “Install_Files” folder on the SL-5500.
The file will be transferred into the SL-5500 memory.

Note: *If there is a PC card slot on the PC you are using, instead of using the Zaurus File Transfer procedure above, you can copy the software onto a memory card, then insert the memory card into the SL-5600. You can then continue with the following steps.*

8. Install software you copied onto the SL-5500 for use with the Add/Remove Software application (see the section on “Installing Package files” in “Add/Remove Software” in the Operation Manual).
Select “Internal Storage” on the Select Install Storage screen.

SHARP CORPORATION